



Customer and Market Operations
EMEA Customer Care

Service Bulletin No. SB-003/29.01.09

RH-59

SERVICE DEVICES, SPARE PARTS AND SWAP PACKAGES FOR RH-59 (LEVEL 2)

Version history:		
Version 9	29.01.09	Code for France SWAP package removed
Version 8	31.08.07	Code for S-Africa SWAP package removed
Version 7	21.02.07	Code for Turkey SWAP package removed
Version 6	11.12.06	Code for locking clip changed (9560206 -> 9900327)
Version 5	06.10.06	Code for Ukraine SWAP package removed
Version 4	01.08.06	Code for grey-black assemblies added
Version 3	12.04.05	Code for screws changed (6290083 -> 6380339)
Version 2	26.11.04	SS-43 (Domesheet alignment jig) added
Version 1	15.10.04	Initial version

Service devices:

PRODUCT	TYPE	CODE	NOTE
POS Flash Dongle (includes ACF-8 Universal Power Supply)	FLS-4S	-	Not available anymore
Universal Power Supply	ACF-8	0680032	
Service Cable	XCS-1	0730218	
Soldering Rework Jig	RJ-12	0770740	
POS Flash Adapter	SF-10	0770748	
Opening Tool	SRT-6	0770431	
Domesheet Alignment Jig	SS-43	0780451	

New service devices for RH-59 are marked with **bold text**.

Lead free rework must be used when repairing RH-59 phones.

☐ Level 1 ☒ Level 2 ☐ Level 3 ☐ Level 4

Version 9



In addition to above-mentioned service devices, following accessories are needed:

TYPE	DESCRIPTION
BL-5C	BATTERY PACK
ACP-8E (Euro)	AC TRAVEL CHARGER
ACP-8X (UK)	AC TRAVEL CHARGER
HDC-5	HEADSET

More detailed information e.g. for flash concept can be found from Level 1 & 2 Service Manual on NOL.



Spare parts for RH-59:

Note: Components in following list marked with **bold text** are new components, which have not been used in other older phone models.

		CMO/EMEA CUSTOMER CARE SALO		
		(LEVEL 2) SPARE PARTS LIST FOR		
		TRANSCEIVER RH-59 NOKIA 2600		
ITEM	CODE	DESCRIPTION	UNIT	NOTE
-	026411 2	D COVER SPARE PART	PC	
I001	026609 2	A COVER ASSY PAINTED IRON BLUE	PC	
I019	026630 2	B COVER ASSY PAINTED IRON BLUE	PC	
I001	026631 7	A COVER ASSY PAINTED LIME TREE GREEN	PC	
I001	026631 9	A COVER ASSY PAINTED TIN GREY	PC	
I019	026632 3	B COVER ASSY PAINTED LIME TREE GREEN	PC	
I019	026632 5	B COVER ASSY PAINTED TIN GREY	PC	
I001	026633 7	A COVER ASSY GREY-BLACK	PC	
I007	485083 5	LCD MOD 130X130 4KCO CSTN SAMSUNG S9.0	PC	
V318	486541 3	LED WHITE 85-169MCD 9MA 90DEG 1608	PC	
V319	486541 3	LED WHITE 85-169MCD 9MA 90DEG 1608	PC	
V322	486541 3	LED WHITE 85-169MCD 9MA 90DEG 1608	PC	
V323	486541 3	LED WHITE 85-169MCD 9MA 90DEG 1608	PC	
F100	511902 9	SM FUSE F 1.5A 32V ROHS-FREE 0603	PC	
I005	514025 1	EARPIECE105+-3DB32RD8.1X2.25 PICO	PC	
I012	514029 1	BEETLE EMC MICROPHONE MOD -42DB	PC	
I013	546933 3	SYST.CONN 2DC+JACK 12VDC 3A	PC	
I017	565003 9	ANTENNA INT EGSM/PCN P2110	PC	
I003	638033	SCREW M1.8X5.3 ISO898-1 REMFORM T6	PC	

NOKIA

	9	CLEAR		
I019	9454357	B COVER IML GREY-BLACK	PC	
I004	9590341	C COVER UI FRAME ASSEMBLY	PC	
I009	9795410	DOMESHEET METAL	PC	
I002	9797217	KEYMAT T9 ASSY HARDTOP LATIN GRAPHITE	PC	
I002	9797224	KEYMAT T9 ASSY ARABIC GRAPHITE	PC	
I002	9797226	KEYMAT T9 ASSY CYRILLIC GRAPHITE	PC	
I002	9797228	KEYMAT T9 ASSY GREEK GRAPHITE	PC	
I002	9797229	KEYMAT T9 ASSY HEBREW GRAPHITE	PC	
I006	9900327	LOCKING CLIP PLASTIC FOR TONGBAO	PC	

When repairing RH-59 phones lead free rework method must be used.

SWAP packages:

CODE	DESCRIPTION
0086284	N2600 RH-59 SWAP ENGINE E&A
0086287	N2600 RH-59 SWAP ENGINE RUSSIA

All SWAP packages include SWAP engine without A-cover (I001), B-cover assy (I019) and keymat (I002).